

パワーチャック用ハードジョー把握範囲一覧 (ジョー型式をクリックすると各ジョーの寸法図を表示します。)

チャック	ジョー	外径把握								内径把握				ハードジョー外径把握可動範囲
		A1	Fig.NO.	A2	Fig.NO.	A3	Fig.NO.	A4	Fig.NO.	B1	Fig.NO.	B2	Fig.NO.	ハードジョー内径把握可動範囲
BB206	HB06A1	23-45	9	---	---	104-126	11	---	---	81-103	9	---	--	23-45,63-85,104-126,144-166
		63-85	10	---	---	144-166	12	---	---	121-143	10	---	--	81-103,121-143
BB206	HB06B1	19-41	5	36-58	5	26-48	7	52-74	7	134-156	5	---	--	19-114
		59-81	6	76-98	6	66-88	8	92-114	8	---	--	---	--	134-156
BB208	HB08B1	11-38	5	35-62	5	25-52	7	59-86	7	167-194	5	---	--	11-136
		61-88	6	85-112	6	75-102	8	109-136	8	---	--	---	--	167-194
BB208	HB08N1	33-60	1	11-38	3	83-110	3	111-138	3	114-141	1	142-169	1	11-60,61-110,111-160,161-188
		83-110	2	61-88	4	133-160	4	161-188	4	164-191	2	---	--	114-141,142-191
BB210	HB10AA1	15-55	1	40-80	3	126-166	3	160-200	3	106-145	1	140-179	1	15-226
		75-115	2	100-140	4	186-226	4	---	--	166-205	2	200-239	2	106-239
BB212	HB12N1	53-118	9	---	---	184-249	11	---	---	144-209	9	---	--	53-178,184-309
		113-178	10	---	---	244-309	12	---	---	204-269	10	---	--	144-269

