

パワーチャック用ハードジョー把握範囲一覧 (ジョー型式をクリックすると各ジョーの寸法図を表示します。)

チャック	ジョー	外径把握								内径把握				ハードジョー外径把握可動範囲
		A1	Fig.NO.	A2	Fig.NO.	A3	Fig.NO.	A4	Fig.NO.	B1	Fig.NO.	B2	Fig.NO.	ハードジョー内径把握可動範囲
BL-206	HB06A1	14-40	9	---	--	101-122	11	---	---	72-98	9	---	---	14-40,54-80,101-122,135-162
		54-80	10	---	--	135-162	12	---	--	112-138	10	---	--	72-98,112-138
BL-206	HB06B1	16-37	5	33-54	5	17-44	7	43-70	7	131-151	5	---	--	16-110
		50-77	6	67-94	6	57-84	8	83-110	8	---	--	---	--	131-151
BL-208	HB08A1	30-64	1	16-50	3	78-112	3	114-148	3	109-143	1	146-179	1	16-64,66-162,164-198
		80-114	2	66-100	4	128-162	4	164-198	4	159-193	2	---	--	109-143,146-193
BL-210	HB10A1	17-63	1	33-82	3	119-168	3	153-202	3	101-147	1	135-181	1	17-228
		74-123	2	93-142	4	179-228	4	---	--	158-207	2	192-241	2	101-241
BL-212	HB12N1	39-114	9	---	--	170-245	11	---	---	131-205	9	---	---	39-245
		99-174	10	---	--	---	--	---	--	191-265	10	---	--	131-265

