

パワーチャック用ハードジョー把握範囲一覧 (ジョー型式をクリックすると各ジョーの寸法図を表示します。)

チャック	ジョー	外径把握								内径把握				ハードジョー外径把握可動範囲
		A1	Fig.NO.	A2	Fig.NO.	A3	Fig.NO.	A4	Fig.NO.	B1	Fig.NO.	B2	Fig.NO.	ハードジョー内径把握可動範囲
BS306	HB06A1	18-43	9	---	---	99-124	11	---	---	76-101	9	---	--	18-43,58-83,99-124,139-164
		58-83	10	---	---	139-164	12	---	---	116-141	10	---	--	76-101,116-141
BS306	HB06B1	14-39	5	31-56	5	21-46	7	47-72	7	136-161	5	---	--	14-112
		54-79	6	71-96	6	61-86	8	87-112	8	---	--	---	--	136-161
BS308	HB08B1	10-34	5	34-58	5	21-48	7	55-82	7	166-200	5	---	--	10-132
		57-84	6	81-108	6	71-98	8	105-132	8	---	--	---	--	166-200
BS310	HB10AA1	14-54	1	36-79	3	122-165	3	156-199	3	105-144	1	139-178	1	14-225
		71-114	2	96-139	4	182-225	4	---	--	162-204	2	196-238	2	105-238

