

パワーチャック用ハードジョー把握範囲一覧 (ジョー型式をクリックすると各ジョーの寸法図を表示します。)

チャック	ジョー	外径把握								内径把握				ハードジョー外径把握可動範囲
		A1	Fig.NO.	A2	Fig.NO.	A3	Fig.NO.	A4	Fig.NO.	B1	Fig.NO.	B2	Fig.NO.	ハードジョー内径把握可動範囲
NL06	HB06A1	22-38	9	---	---	103-120	11	---	---	80-96	9	---	---	22-38,62-78,103-120,143-160
		62-78	10	---	---	143-160	12	---	---	120-136	10	---	---	80-96,120-136
NL06	HB06B1	18-35	5	35-52	5	25-42	7	51-68	7	133-149	5	---	---	18-108
		58-75	6	75-92	6	65-82	8	91-108	8	---	--	---	---	133-149
NL08	HB08A1	28-55	1	14-41	3	76-103	3	112-139	3	107-134	1	143-170	1	14-55,64-105,112-153,162-189
		78-105	2	64-91	4	126-153	4	162-189	4	157-184	2	---	---	107-134,143-184
NL10	HB10A1	15-55	1	28-74	3	114-160	3	148-194	3	99-139	1	133-173	1	15-220
		69-115	2	88-134	4	174-220	4	---	---	153-199	2	187-233	2	99-233
NL12	HB12B1	47-118	9	---	---	171-242	11	---	---	123-194	9	---	---	47-302
		107-178	10	---	---	231-302	12	---	---	183-254	10	---	---	123-254

